

VPX998B

Loopback and breakout I/O for 6U VPX Modules

VPX998B



vadatech
THE POWER OF VISION

Key Features

- 6U VPX Front Module for test and validation of the backplane
- Loopback and Breakout I/O for a 6U VPX

Benefits

- Design utilizes proven VadaTech subcomponents and engineering techniques
- Electrical, mechanical, software, and system-level expertise in house
- Full system supply from industry leader
- AS9100 and ISO9001 certified company

OpenVPX™



VPX998B

The VPX998B is a loop-back and break-out panel for a 6U VPX Module.

The VPX998B is utilized for test/validation of the high speed SERDES of a 6U VPX backplane. The VPX998B via zero-ohm resistors routes the P1/P2 /P4/P5 and P6 of the front module high speed SERDES TX+/- to its RX+/- . Total of 96 loop-back which covers all the 96 SERDES (TX/RX) of the front module. The zero ohms resistors could be removed to reduce the number of lanes.

The Module also brings out the JTAG as well as the two VPX P0 clocks into a Twinax connector. In addition, the Module brings out the NVROM/*SYSREST/*SYSCON to the panel for ease of access. The VPX geographic address could be set by an on-board switch to a unique address.

The P0 power is brought to test points for ease of measurement.

The VPX998B has high speed VPX connector for test/validation of 25G SERDES on the backplane.

Figure 1: VPX998B

Specifications

Architecture	
Physical	Dimensions 6U
Type	Breakout Panel
Standards	
VPX	Type VITA46.x
VPX	Type VITA 65 OpenVPX
VPX	Panel Profile See Ordering Options
Configuration	
Power	N/A
Rear Panel	Interface Connector Toggle switches JTAG
Other	
MTBF	MIL Hand book 217-F@ TBD hrs
Certifications	Designed to meet FCC, CE and UL certifications, where applicable
Standards	VadaTech is certified to both the ISO9001:2015 and AS9100D standards
Warranty	Two (2) years, see VadaTech Terms and Conditions

INTEGRATION SERVICES AND APPLICATION-READY PLATFORMS

VadaTech has a full ecosystem of ATCA and MTCA products including chassis platforms, shelf managers, AMC modules, Switch and Payload Boards, Rear Transition Modules (RTMs), Power Modules, and more. The company also offers integration services as well as pre-configured Application-Ready Platforms. Please contact VadaTech Sales for more information.

Ordering Options

VPX998B – A00-000-G00

A = Loop back option		G = Slot Profile
0 = P1/P2/P3/P4/P5/P6/P7/P8 loop back 1 = Loop back follows note in figure 2 of the diagram 2 = Reserved 3 = Reserved		0 = 5 HP 1 = Reserved

Contact

VadaTech Corporate Office

198 N. Gibson Road, Henderson, NV 89014

Phone: +1 702 896-3337 | Fax: +1 702 896-0332

Asia Pacific Sales Office

7 Floor, No. 2, Wenhua Street, Neihu District, Taipei 114, Taiwan

Phone: +886-2-2627-7655 | Fax: +886-2-2627-7792

VadaTech European Sales Office

VadaTech House, Bulls Copse Road, Southampton, SO40 9LR

Phone: +44 2380 016403

info@vadatech.com | www.vadatech.com

Choose VadaTech

We are technology leaders

- First-to-market silicon
- Constant innovation
- Open systems expertise

We commit to our customers

- Partnerships power innovation
- Collaborative approach
- Mutual success

We deliver complexity

- Complete signal chain
- System management
- Configurable solutions

We manufacture in-house

- Agile production
- Accelerated deployment
- AS9100 accredited



vadatech
THE POWER OF VISION

Trademarks and Disclaimer

The VadaTech logo is a registered trademark of VadaTech, Inc. Other registered trademarks are the property of their respective owners. AdvancedTCA™ and the AdvancedMC™ logo are trademarks of the PCI Industrial Computers Manufacturers Group. All rights reserved. Specification subject to change without notice.

© 2020 VadaTech Incorporated. All rights reserved.
DOC NO. 4FM737-12 REV 01 | VERSION 1.1 – JUN/24